

User Guide

### Operation Guide

#### Step 1:

Download Aztech Kyla App from Google Play/App Store



#### Step 2:

Plug-in the Smart WiFi Plug into a wall socket

### Step 3:

Login to Aztech Kyla App, then add "Smart WiFi Plug" to device list to enable the device...

#### Step 4:

After plugging, a rapid flashing RED LED light will show on the Smart WiFi Plug's ON/OFF button. If not, please check your power or press and hold the ON/OFF button for 6 seconds until you see a rapid flashing RED LED light.

#### Step 5:

Connect your smart phone or tablet device to the router or modem with internet and WiFi access.

#### Step 6:

Follow the App instruction for first time setup.


#### Restore Default Setting

Press and hold the Smart WiFi Plug's ON/OFF button for 6 sec until you see a rapid flashing RED LED light.

Note: Maximum power should be no more than 3120W, and maximum circuit should be no more than 13A, otherwise overheating may cause fire. Do not use in a wet place such as bathroom.

#### **Product Description**

The Smart WiFi Plug can be used to controlled any on/off device when plugged in using the App, giving you the power to control your device anytime or anywhere.



#### **Product Features**

Remote Control: Turn on/off the Smart

WiFi Plug via mobile App while connected to WiFi

Timer: Set a timer to turn on/off the Smart WiFi Plug via

mobile App

Countdown: Set a countdown to turn on/off the Smart.

WiFi Plug via mobile App



Smart WiFi Plug

Thanks for using Aztech Kyla product If you need support or help, please visit www.kyla.aztech.com

## **Technical Specifications**

Input/Output Voltage:	100-240V~ 50Hz,13A
No. of Operating Cycles:	1E4
Circuit Disconnection:	Micro-Disconnection
Insulating Materials:	PTI175
Glow-wire Temperature:	Level 2, 750°C
Type of Switch:	Single-Pole
Cooling Condition:	Not Required
	Forced Cooling

# **Aztech**

©2018 Aztech Technologies Pte Ltd. All rights reserved.